arXiv:1006.0329v1 [math.NA] 2 Jun 2010

Mathematical and Numerical Studies on Meshless Methods for Exterior Unbounded Domain Problems

Takemi Shigeta, D. L. Young*

Department of Civil Engineering and Hydrotech Research Institute
National Taiwan University
No. 1, Sec. 4, Roosevelt Road, Taipei 10617, Taiwan

Abstract

The method of fundamental solution (MFS) is an efficient meshless method for solving a boundary value problem in an exterior unbounded domain. The numerical solution obtained by the MFS is accurate, while the corresponding matrix equation is ill-conditioned. A modified MFS (MMFS) with the proper basis functions is proposed by the introduction of the modified Trefftz method (MTM). The concrete expressions of the corresponding condition numbers and the solvability by these methods are mathematically proven. Thereby, the optimal parameter minimizing the condition number is also mathematically given. Numerical experiments show that the condition numbers of the matrices corresponding to the MTM and the MMFS are reduced and that the numerical solution by the MMFS is more accurate than the one by the conventional method.

Keywords: Exterior unbounded domain, Condition number, Laplace equation, Method of fundamental solution, Modified Trefftz method,

---

1. Introduction

The method of fundamental solutions (MFS) is a truly meshless numerical method for easily and rapidly solving boundary value problems of elliptic type. The approximate solution by the MFS is expressed by a linear combination of fundamental solutions to a partial differential equation. Hence, the approximate solution automatically satisfies the partial differential equation, and it remains to consider boundary conditions. In this sense, the MFS is a boundary method like the boundary element method (BEM). The BEM requires singular integrals, while the MFS does not require any treatments for the singularity of the fundamental solutions, which is an advantage of the MFS.

---

*Corresponding author.
Email addresses: `shigeta@ntu.edu.tw` (Takemi Shigeta), `dlyoung@ntu.edu.tw` (D. L. Young)

Mathon and Johnston [8] first obtained numerical solutions by applying the MFS. Bogomolny [1] proved the convergence property. Katsurada and Okamoto [4], [6] proved uniqueness of numerical solutions and the convergence property, and mathematically discussed the suitable distribution of source points.

Another advantage of the MFS is to directly solve exterior problems, which is different from the finite element method (FEM) and other meshless methods using radial basis functions. Actually, the MFS can be applied directly to the exterior problems to obtain accurate solutions. Even though the basis functions used in the MFS do not satisfy a condition at infinity, the accuracy is not bad in the whole computational domain. Katsurada [5] proposed that the approximate solution for the exterior problems should be defined by a linear combination of the proper basis functions satisfying the governing equation as well as the condition at infinity. Although many researchers seem to still use the MFS with the conventional basis functions, we should use the MFS with the proper basis functions to obtain more accurate solutions in the whole domain.

On the other hand, the Trefftz method is also known as a numerical meshless method for solving boundary value problems. The approximate solution by the Trefftz method is expressed by a linear combination of functions satisfying the governing equation. Hence, similar to the MFS, it is sufficient if the boundary condition is considered. This method is also regarded as a boundary method.

It is well known that the coefficient matrices derived from the MFS and the Trefftz method are highly ill-conditioned. Numerical solutions to the ill-conditioned matrix equations are unstable. We need to improve the ill-conditioning.

Ramachandran [9] applied the singular value decomposition (SVD) to the MFS to improve the accuracy. Chen *et al.* [2], [3] discussed the equivalence between the Trefftz method and the MFS. Liu [7] proposed the modified MFS (MMFS) for interior problems by introducing the modified Trefftz method (MTM). Both of the MTM and the MMFS can drastically reduce the condition numbers of the corresponding matrices.

In this paper, we propose a modified MFS for solving the exterior problem according to the papers cited above. The solution of the exterior problem defined in Section 2 is discretized by the MFS with the proper basis functions satisfying the condition at infinity in Section 3. Section 4 proposes a modified MFS based on the modified Trefftz method with a characteristic length, which plays an important role for the condition number. Section 5 shows some mathematical results about the condition numbers and the uniqueness of the approximate solutions by the MTM and MMFS. Thereby, the optimal characteristic length that minimizes the condition number corresponding to the MTM can explicitly be given in a mathematical form. Section 6 shows the effectiveness of the MTM and the MMFS through numerical experiments.

2. Problem Setting

Let Ω_0 be a two dimensional bounded domain enclosed by the boundary $\Gamma = \{(r, \theta) : r = \rho(\theta),\ 0 \leq \theta < 2\pi\}$ in the polar representation, where $\rho(\theta)$ is a smooth function. Let $\Omega := \boldsymbol{R}^2 \setminus \overline{\Omega_0}$ be the unbounded domain outside the domain Ω_0. Then, we consider the following exterior Dirichlet problem of the Laplace equation: find $u \in C^2(\Omega) \cap C(\overline{\Omega})$ such that

$$\Delta u = 0 \qquad \text{in} \quad \Omega, \tag{1}$$

$$u = f \qquad \text{on} \quad \Gamma, \tag{2}$$

$$u(\boldsymbol{x}) = O(|\boldsymbol{x}|^{-1}) \quad \text{as} \quad |\boldsymbol{x}| \to \infty, \tag{3}$$

where f is a continuous function defined on Γ.

From now on, we identify the Cartesian plane $\boldsymbol{R}^2$ with the complex plane $\boldsymbol{C}$. We denote the (j, k) component of a matrix Q by $Q_{j,k}$.

3. Discretization by the Method of Fundamental Solutions (MFS)

3.1. The conventional MFS with the conventional basis functions

The fundamental solution of the Laplace equation in two dimensions is defined as

$$G^*(r) := -\frac{1}{2\pi} \ln r$$

for $r = |z| = \sqrt{x^2 + y^2}$, which is a solution to

$$-\Delta G^*(r) = \delta(r)$$

with the Dirac delta distribution δ.

We distribute the source points $\{\zeta_j\}_{j=1}^N$ along a circle outside the domain Ω. The basis functions are defined as

$$G_j(z) := -2\pi G^*(|z - \zeta_j|) = \ln |z - \zeta_j|; \qquad \{\zeta_j\}_{j=1}^N \subset \overline{\Omega}^c = \Omega_0. \tag{4}$$

Then, the exact solution u can be approximated by a linear combination of the basis functions $\{G_j\}_{j=1}^N$ as follows:

$$u(z) \approx u_N(z) := \sum_{j=1}^{N} w_j G_j(z), \qquad \forall z \in \overline{\Omega}, \tag{5}$$

where $\{w_j\}_{j=1}^N \subset \boldsymbol{R}$ are expansion coefficients to be determined below. Since the basis functions (4) have no singular points in Ω, the approximate solution u_N satisfies the Laplace equation (1) in the domain Ω. It remains to consider the boundary condition to find $\{w_j\}_{j=1}^N$. We use the boundary collocation method since it is impossible that u_N exactly satisfies the boundary condition. We distribute the collocation points $\{z_k\}_{k=1}^N$ on the boundary Γ. Substituting (5) at the collocation points into (2), we have

$$\sum_{j=1}^{N} w_j G_j(z_k) = f(z_k), \quad k = 1, 2, \ldots, N; \qquad \{z_k\}_{k=1}^N \subset \Gamma$$

or in the matrix form:

$$A\boldsymbol{w} = \boldsymbol{f}, \tag{6}$$

where the matrix $A = (A_{k,j}) \in \boldsymbol{R}^{N\times N}$ and the vectors $\boldsymbol{w} = (w_j) \in \boldsymbol{R}^N$, $\boldsymbol{f} = (f_k) \in \boldsymbol{R}^N$ are defined by

$$\begin{aligned} A_{k,j} &:= G_j(z_k), \quad k = 1, 2, \ldots, N;\ j = 1, 2, \ldots, N, \\ f_k &:= f(z_k), \qquad k = 1, 2, \ldots, N. \end{aligned}$$

If A is not singular, we can solve (6) and obtain the approximate solution u_N by substituting $\boldsymbol{w}$ into (5).

For any point $z = re^{i\theta} \in \Omega$ and the source point $\zeta_j = Re^{i\phi_j} \in \Omega_0$ with the imaginary unit $i = \sqrt{-1}$, we have

$$\begin{aligned} |z - \zeta_j|^2 &= |re^{i\theta} - Re^{i\phi_j}|^2 = r^2 + R^2 - 2rR\cos(\theta - \phi_j) \\ &= O(r^2), \qquad r \to \infty, \end{aligned}$$

from which we know

$$G_j(z) = \ln|z - \zeta_j| = O(\ln r), \qquad r \to \infty.$$

Hence, we obtain

$$u_N(z) = \sum_{j=1}^{N} w_j G_j(z) = O(\ln r), \qquad r \to \infty, \tag{7}$$

which does not satisfy the condition (3). Therefore, the basis functions (4) are not proper for the exterior problem.

3.2. The conventional MFS with modified basis functions

We need to use another basis functions to approximate a solution that converges to zero at infinity. We define the following modified basis functions [5]:

$$\widehat{G}_j(z) = \ln\frac{|z - \zeta_j|}{|z|} = \ln|z - \zeta_j| - \ln|z|, \tag{8}$$

where $\widehat{G}_j(z)$ satisfies $\Delta\widehat{G}_j = 0$ in Ω since both of $\ln|z - \zeta_j|$ and $\ln|z|$ are the fundamental solutions. For any point $z = re^{i\theta} \in \Omega$ and the source point $\zeta_j = Re^{i\phi_j} \in \Omega_0$, we have

$$\begin{aligned} \frac{|z - \zeta_j|^2}{|z|^2} &= \frac{r^2 + R^2 - 2rR\cos(\theta - \phi_j)}{r^2} \\ &= 1 + \left(\frac{R}{r}\right)^2 - 2\left(\frac{R}{r}\right)\cos(\theta - \phi_j) \\ &= 1 + O(r^{-1}), \qquad r \to \infty, \end{aligned}$$

from which we know

$$\widehat{G}_j(z) = \ln \frac{|z-\zeta_j|}{|z|} = \ln \sqrt{1+O(r^{-1})} = O(r^{-1}), \qquad r \to \infty. \tag{9}$$

Hence, we obtain

$$u_N(z) = \sum_{j=1}^{N} w_j \widehat{G}_j(z) = O(r^{-1}), \qquad r \to \infty,$$

which satisfies the condition (3). Therefore, we can see that (8) are the proper basis functions for solving the exterior problem. In this paper, the approximate solution

$$\widehat{u}_N(z) = \sum_{j=1}^{N} w_j \widehat{G}_j(z), \qquad \forall z \in \overline{\Omega} \tag{10}$$

is called the MFS with the modified basis functions. When we use this method, in (6) we replace the matrix A into $\widehat{A}$ defined by $\widehat{A}_{k,j} := \widehat{G}_j(z_k)$.

4. A modified MFS with modified basis functions

4.1. The modified Trefftz method (MTM)

The approximate solution by the modified Trefftz method (MTM) [7] is given by

$$\widetilde{u}_M(r,\theta) := a_0 + \sum_{k=1}^{M} (a_k \cos k\theta + b_k \sin k\theta) \left(\frac{R_0}{r}\right)^k, \quad r \geq \rho(\theta), \quad 0 \leq \theta < 2\pi, \tag{11}$$

where the characteristic length R_0 is often taken as

$$R_0 \leq \rho_{\min} := \min_{0 \leq \theta < 2\pi} \rho(\theta). \tag{12}$$

This method is reduced to the conventional Trefftz method if $R_0 = 1$. We can see that (3) implies that $a_0 = 0$. But, we treat a_0 as an unknown coefficient for reasons of expediency (see Remark 1). Using the boundary collocation method, we have

$$\widetilde{u}_M(\rho_j,\theta_j) = a_0 + \sum_{k=1}^{M} (a_k \cos k\theta_j + b_k \sin k\theta_j) \left(\frac{R_0}{\rho_j}\right)^k = g_j, \quad j = 1, 2, \ldots, N, \tag{13}$$

where

$$\rho_j := \rho(\theta_j), \quad g_j := f(\theta_j), \quad \theta_j := 2\pi(j-1)/N.$$

Therefore, we obtain the matrix equation:

$$S\boldsymbol{y} = \boldsymbol{g}, \tag{14}$$

where

$$\boldsymbol{y} := (a_0, a_1, b_1, \ldots, a_M, b_M)^T \in \boldsymbol{R}^{2M+1}, \qquad \boldsymbol{g} := (g_1, g_2, \ldots, g_N)^T \in \boldsymbol{R}^N$$

and $S \in \boldsymbol{R}^{N\times(2M+1)}$ is defined by

$$S_{j,1} := 1, \quad S_{j,2k} := \left(\frac{R_0}{\rho_j}\right)^k \cos k\theta_j, \quad S_{j,2k+1} := \left(\frac{R_0}{\rho_j}\right)^k \sin k\theta_j$$
$$(j = 1, 2, \ldots, N;\ k = 1, 2, \ldots, M).$$

When R_0 satisfies (12), every element of S is less than or equal to 1. We take $N = 2M + 1$ to make S a square matrix.

Let $z_j = \rho_j e^{i\theta_j}$ in (6). Then, $\boldsymbol{f}$ coincides with $\boldsymbol{g}$.

Remark 1. Since we know that $a_0 = 0$, the number of unknown coefficients are $2M$ in essentials. We can remove the first column of S, which we denote by S'. If we consider the square matrix $S' \in \boldsymbol{R}^{2M\times N}$ with $N = 2M$, then we can see that

$$\sin M\theta_j = \sin M\frac{2\pi(j-1)}{N} = \sin \pi(j-1) = 0 \qquad (j = 1, 2, \ldots, N),$$

which implies $S'_{j,2M} = 0$ for $j = 1, 2, \ldots, N$. Hence, S' becomes singular. Although we can avoid the singularity of S' by taking $\theta_j = 2\pi(j-1)/(N+1)$, we treat a_0 as an unknown coefficient to use S in this paper.

4.1.1. Transformation of the MFS to the MTM

The modified basis function for the source point $\zeta = Re^{i\phi}$ can be transformed as follows:

$$\begin{aligned}
\ln\frac{|z-\zeta|}{|z|} &= \ln\frac{|re^{i\theta} - Re^{i\phi}|}{|re^{i\theta}|} = \ln\left|1 - \frac{R}{r}e^{i(\phi-\theta)}\right| \\
&= \operatorname{Re}\ln\left(1 - \frac{R}{r}e^{i(\phi-\theta)}\right) = -\operatorname{Re}\sum_{k=1}^{\infty}\frac{1}{k}\left(\frac{R}{r}e^{i(\phi-\theta)}\right)^k \\
&= -\operatorname{Re}\sum_{k=1}^{\infty}\frac{1}{k}\left(\frac{R}{r}\right)^k e^{ik(\phi-\theta)} = -\sum_{k=1}^{\infty}\frac{1}{k}\left(\frac{R}{r}\right)^k \cos k(\phi-\theta) \\
&= -\sum_{k=1}^{\infty}\frac{1}{k}\left(\frac{R}{r}\right)^k \cos k(\theta-\phi).
\end{aligned}$$

Hence, we can write the approximate solution by the MFS in the form:

$$\begin{aligned}
u_N(r,\theta) &= \sum_{j=1}^{N} w_j \ln\frac{|z-\zeta_j|}{|z|} &(15)\\
&= \sum_{j=1}^{N} w_j \left[-\sum_{k=1}^{\infty}\frac{1}{k}\left(\frac{R}{r}\right)^k \cos k(\theta-\theta_j)\right], &(16)
\end{aligned}$$

where we put $\zeta_j = Re^{i\theta_j}$ with $\theta_j = 2\pi(j-1)/N$ $(j = 1, 2, \ldots, N)$. If we use the conventional basis functions, the approximate solution can be written in the form:

$$u_N(r,\theta) = \sum_{j=1}^{N} w_j \ln|z - \zeta_j| \tag{17}$$

$$= \sum_{j=1}^{N} w_j \left[\ln r - \sum_{k=1}^{\infty} \frac{1}{k}\left(\frac{R}{r}\right)^k \cos k(\theta - \theta_j)\right]. \tag{18}$$

We know from (7) that (17) or (18) does not satisfy (3). But, if we impose the condition

$$\sum_{j=1}^{N} w_j \ln r = 0 \qquad (r \neq 1)$$

or

$$\sum_{j=1}^{N} w_j = 0, \tag{19}$$

then (18) coincides with (16). Hence, we know that (18) satisfies (3) as long as (19) is imposed.

On the boundary

$$\Gamma = \{(r,\theta) : r = \rho(\theta), \quad 0 \leq \theta < 2\pi\},$$

the approximate solution (16) is written as

$$\begin{aligned} u_N(\rho(\theta),\theta) &= \sum_{j=1}^{N} w_j \left[-\sum_{k=1}^{\infty} \frac{1}{k}\left(\frac{R}{\rho(\theta)}\right)^k \cos k(\theta - \theta_j)\right] \\ &= -\sum_{k=1}^{\infty}\sum_{j=1}^{N} w_j \frac{1}{k}\left(\frac{R}{\rho(\theta)}\right)^k (\cos k\theta \cos k\theta_j + \sin k\theta \sin k\theta_j) \\ &= -\sum_{k=1}^{\infty}\sum_{j=1}^{N} w_j \frac{1}{k}\left(\frac{R}{R_0}\right)^k (\cos k\theta_j \cos k\theta + \sin k\theta_j \sin k\theta)\left(\frac{R_0}{\rho(\theta)}\right)^k. \end{aligned} \tag{20}$$

Truncating the infinite series $\sum_{k=1}^{\infty}$ in (20) into a finite series $\sum_{k=1}^{M}$:

$$u_N(\rho(\theta),\theta) \approx -\sum_{k=1}^{M}\sum_{j=1}^{N} w_j \frac{1}{k}\left(\frac{R}{R_0}\right)^k (\cos k\theta_j \cos k\theta + \sin k\theta_j \sin k\theta)\left(\frac{R_0}{\rho(\theta)}\right)^k, \tag{21}$$

and comparing (21) with (11), we obtain

$$a_k = -\frac{1}{k}\left(\frac{R}{R_0}\right)^k \sum_{j=1}^{N} w_j \cos k\theta_j, \qquad k = 1, 2, \ldots, M, \tag{22}$$

$$b_k = -\frac{1}{k}\left(\frac{R}{R_0}\right)^k \sum_{j=1}^{N} w_j \sin k\theta_j, \qquad k = 1, 2, \ldots, M. \tag{23}$$

Adding the condition (19) to (22) and (23), we obtain the following matrix equation:

$$\boldsymbol{y} = K\boldsymbol{w}, \tag{24}$$

where $K \in \boldsymbol{R}^{(2M+1)\times N}$ is defined by

$$K_{1,j} := 1, \quad K_{2k,j} := -\frac{1}{k}\left(\frac{R}{R_0}\right)^k \cos k\theta_j, \quad K_{2k+1,j} := -\frac{1}{k}\left(\frac{R}{R_0}\right)^k \sin k\theta_j \\ (k = 1, 2, \ldots, M;\ j = 1, 2, \ldots, N).$$

Substituting (24) into (14), we obtain the matrix equation

$$SK\boldsymbol{w} = \boldsymbol{f}. \tag{25}$$

Remark 2. When we consider (16), it is not necessary to impose (19) in essentials. In addition, we know that $a_0 = 0$. Hence, we can remove the first row of K, which is denoted by $K' \in \boldsymbol{R}^{2M\times N}$. Then, the square matrix K' with $N = 2M$ becomes singular because of the same reason described in Remark 1. Therefore, we impose the condition (19) to use K.

The matrix K for $R_0 = 1$, denoted by K_1, becomes

$$K_{1,j} = 1, \quad K_{2k,j} = -\frac{1}{k}R^k \cos k\theta_j, \quad K_{2k+1,j} = -\frac{1}{k}R^k \sin k\theta_j \\ (k = 1, 2, \ldots, M;\ j = 1, 2, \ldots, N),$$

while K for $R_0 = R$, denoted by K_2, becomes

$$K_{1,j} = 1, \quad K_{2k,j} = -\frac{1}{k}\cos k\theta_j, \quad K_{2k+1,j} = -\frac{1}{k}\sin k\theta_j \\ (k = 1, 2, \ldots, M;\ j = 1, 2, \ldots, N),$$

which is independent of R.

After obtaining the unknown vector $\boldsymbol{w}$, we substitute $\boldsymbol{w}$ into (15) not (21). We call this method the modified MFS (MMFS). Even if we substitute $\boldsymbol{w}$ into (21), the result should be the same as the result when we use (13).

Remark 3. We can see that $SK \in \boldsymbol{R}^{N\times N}$ is always a square matrix for any M. Since we would like to find unknown $\boldsymbol{w}$ from the known $\boldsymbol{f}$, it is not necessary that S and K are square matrices. However, we see from numerical experiments that a better approximate solution can be obtained when the matrices S and K are square. This numerical result is not shown in this paper.

We notice that the matrix SK converges to the matrix A corresponding to the conventional MFS as $M \to \infty$. In this sense, SK can be regarded as an approximation to A.

5. Some Mathematical Results

In this section, we show some theoretical results about the matrices S and K defined in the previous section. In particular, we obtain the optimal R_0 in a mathematical form. We prove the uniqueness of the numerical solutions obtained by the MTM and the MMFS.

The following Propositions 1 and 2 have already been shown in [2] and [7]. In this paper, we give the complete and more simple proof of Proposition 2.

Proposition 1. *The matrix K can be decomposed into*

$$K = T_R T_\theta,$$

where $T_R \in \boldsymbol{R}^{(2M+1)\times(2M+1)}$ and $T_\theta \in \boldsymbol{R}^{(2M+1)\times N}$ are defined as

$$\begin{aligned} &(T_R)_{1,1} = 1, \qquad (T_R)_{k,j} = 0 \quad (k \neq j) \\ &(T_R)_{2k,2k} = (T_R)_{2k+1,2k+1} = -\frac{1}{k}\left(\frac{R}{R_0}\right)^k \quad (k = 1, 2, \ldots, M) \end{aligned}$$

and

$$\begin{aligned} &(T_\theta)_{1,j} = 1 \quad (j = 1, 2, \ldots, N), \\ &(T_\theta)_{2k,j} = \cos k\theta_j, \quad (T_\theta)_{2k+1,j} = \sin k\theta_j \quad (k = 1, 2, \ldots, M;\ j = 1, 2, \ldots, N). \end{aligned}$$

Proposition 2. *The matrix T_θ has the orthogonal property:*

$$T_\theta T_\theta^T = \frac{N}{2}\,\mathrm{diag}(2, 1, \ldots, 1) \in \boldsymbol{R}^{(2M+1)\times(2M+1)}. \tag{26}$$

When $N = 2M+1$, the inverse matrix T_θ^{-1} can be written as

$$\begin{aligned} &(T_\theta^{-1})_{j,1} = \frac{1}{N} \quad (j = 1, 2, \ldots, N), \\ &(T_\theta^{-1})_{j,2k} = \frac{2}{N}\cos k\theta_j, \quad (T_\theta^{-1})_{j,2k+1} = \frac{2}{N}\sin k\theta_j \quad (k = 1, 2, \ldots, M;\ j = 1, 2, \ldots, N). \end{aligned}$$

Proof. Let $\omega := \exp(2\pi i/N)$. Then, we see $\exp(ik\theta_l) = \omega^{k(l-1)}$. We notice that

$$\sum_{l=1}^{N} \omega^{s(l-1)} = \begin{cases} N & (s = mN;\ m = 0, \pm 1, \pm 2, \ldots) \\ 0 & (s \neq mN;\ m = 0, \pm 1, \pm 2, \ldots) \end{cases}$$

since for $s \neq mN$, we can divide the following equation by $\omega^s - 1 \neq 0$:

$$(\omega^s - 1)\left((\omega^s)^{N-1} + (\omega^s)^{N-2} + \cdots + \omega^s + 1\right) = (\omega^s)^N - 1 = 0.$$

Since $T_\theta T_\theta^T$ is symmetric, it is sufficient to calculate the following components:

$$\begin{aligned}
(T_\theta T_\theta^T)_{2k,j} &= \sum_{l=1}^{N} \cos j\theta_l \cos k\theta_l \\
&= \sum_{l=1}^{N} \frac{\omega^{j(l-1)} + \omega^{-j(l-1)}}{2} \frac{\omega^{k(l-1)} + \omega^{-k(l-1)}}{2} \\
&= \frac{1}{4} \sum_{l=1}^{N} [\omega^{(j+k)(l-1)} + \omega^{-(j+k)(l-1)} + \omega^{(j-k)(l-1)} + \omega^{-(j-k)(l-1)}] \\
&= \left\{ \begin{array}{cc} N/2 & (j = k) \\ 0 & (j \neq k) \end{array} \right. .
\end{aligned}$$

In a similar fashion, we have

$$(T_\theta T_\theta^T)_{2k,j+1} = 0, \qquad (T_\theta T_\theta^T)_{2k+1,j+1} = \left\{ \begin{array}{cc} N/2 & (j = k) \\ 0 & (j \neq k) \end{array} \right. .$$

Hence, we obtain (26).

Next, we calculate the inverse of T_θ. Let the matrix D satisfy

$$T_\theta T_\theta^T = \frac{N}{2} \operatorname{diag}(2, 1, \ldots, 1) = D^2, \tag{27}$$

from which we can write

$$D = \sqrt{\frac{N}{2}} \operatorname{diag}(\sqrt{2}, 1, \ldots, 1).$$

Premultiplying and postmultiplying (27) by D^{-1} respectively, we have

$$D^{-1} T_\theta T_\theta^T D^{-1} = I.$$

We then know that $D^{-1} T_\theta$ is an orthogonal matrix:

$$D^{-1} T_\theta (D^{-1} T_\theta)^T = I,$$

from which we have $(D^{-1} T_\theta)^{-1} = (D^{-1} T_\theta)^T$. Therefore, we obtain

$$T_\theta^{-1} = T_\theta^T D^{-2} \tag{28}$$

with

$$D^{-2} := (D^{-1})^2 = \frac{2}{N} \operatorname{diag}(\frac{1}{2}, 1, \ldots, 1).$$

We can obtain all the components of T_θ^{-1} explicitly from (28). □

Remark 4. Arbitrary matrix Q can always be decomposed into

$$Q = UP,$$

where U denotes an orthogonal matrix and P a positive semidefinite symmetric matrix. This is said to be the polar decomposition of Q.

We can redefine the sign of a part of the components of T_R and T_θ as follows:

$$(T_R)_{2k,2k} = (T_R)_{2k+1,2k+1} = \frac{1}{k}\left(\frac{R}{R_0}\right)^k$$
$$(T_\theta)_{2k,j} = -\cos k\theta_j, \quad (T_\theta)_{2k+1,j} = -\sin k\theta_j$$

in Proposition 1. We see that K can be written as $K = (T_R D)(D^{-1}T_\theta)$ with the orthogonal matrix $D^{-1}T_\theta$ and the diagonal matrix $T_R D$ whose diagonal components are positive. Hence, we know that $K^T = (D^{-1}T_\theta)^T(T_R D)$ is the polar decomposition.

In the following proposition, the determinant $\det(T_\theta)$ with $N = 2M+1$ is found in [2] and [7].

Proposition 3. *Let $N = 2M+1$. Then, the determinants of the matrices T_R and T_θ can be given by*

$$\det(T_R) = \frac{1}{(M!)^2}\left(\frac{R}{R_0}\right)^{M(M+1)}, \qquad \det(T_\theta) = \frac{N^{M+1/2}}{2^M}.$$

Hence, $K = T_R T_\theta$ is not singular and K^{-1} can explicitly be written as

$$\begin{aligned}
(K^{-1})_{j,1} &= \frac{1}{N} \quad (j = 1, 2, \ldots, N), \\
(K^{-1})_{j,2k} &= -\frac{2k}{N}\left(\frac{R_0}{R}\right)^k \cos k\theta_j, \\
(K^{-1})_{j,2k+1} &= -\frac{2k}{N}\left(\frac{R_0}{R}\right)^k \sin k\theta_j \quad (j = 1, 2, \ldots, N;\ k = 1, 2, \ldots, M)
\end{aligned}$$

Proof. It is easy to obtain $\det(T_R)$ and $\det(T_\theta)$ by simple calculations:

$$\begin{aligned}
\det(T_R) &= 1 \cdot \prod_{k=1}^{M}\left[-\frac{1}{k}\left(\frac{R}{R_0}\right)^k\right]^2 = \frac{1}{(M!)^2}\left(\frac{R}{R_0}\right)^{2\sum_{k=1}^{M} k} \\
&= \frac{1}{(M!)^2}\left(\frac{R}{R_0}\right)^{M(M+1)}
\end{aligned}$$

and

$$\det(T_\theta) = \sqrt{\det(T_\theta^2)} = \sqrt{\det(T_\theta T_\theta^T)} = \left\{N \cdot \left(\frac{N}{2}\right)^{2M}\right\}^{1/2} = \frac{N^{M+1/2}}{2^M}.$$

From Proposition 2, we can immediately derive all the components of $K^{-1} = T_\theta^{-1}T_R^{-1}$. ☐

We notice that K is independent of the boundary Γ and that K^{-1} is explicitly given, we can always directly obtain $\boldsymbol{w}$ from $\boldsymbol{y}$ without solving (24).

The condition number of a matrix Q corresponding to the p-norm is defined as

$$\mathrm{cond}_p(Q) = \|Q\|_p \|Q^{-1}\|_p,$$

where $\|\cdot\|_p$ is the matrix norm. When $p = 2$, the matrix norm $\|Q\|_2$ is the largest singular value of Q or the square root of the largest eigenvalue of Q^TQ.

Proposition 4. *Let $N = 2M + 1$ and $R_0 = R$. Then, the condition numbers of T_R, T_θ and $K = K_2$ corresponding to the 2-norm are given as*

$$\mathrm{cond}_2(T_R) = M, \qquad \mathrm{cond}_2(T_\theta) = \sqrt{2}, \qquad \mathrm{cond}_2(K_2) = \sqrt{2}M,$$

which are independent of R.

Proof. When we take $R_0 = R$, we have

$$T_R = \mathrm{diag}\left(1, -1, -1, -\frac{1}{2}, -\frac{1}{2}, \dots, -\frac{1}{M}, -\frac{1}{M}\right).$$

We can then easily see that $\|T_R\|_2 = 1$ and $\|T_R^{-1}\|_2 = M$, which follows $\mathrm{cond}_2(T_R) = M$.

We notice that the matrix norm $\|T_\theta\|_2$ is the square root of the largest eigenvalue of $T_\theta T_\theta^T$. Hence, from (26) in Proposition 2, we obtain $\|T_\theta\|_2 = \sqrt{N}$. Similarly, we have $\|T_\theta^{-1}\|_2 = \sqrt{2/N}$. Therefore, we obtain $\mathrm{cond}_2(T_\theta) = \sqrt{2}$.

Next, since T_R and $T_\theta T_\theta^T$ are diagonal matrices, we can calculate

$$\begin{aligned} K_2 K_2^T &= (T_R T_\theta)(T_R T_\theta)^T = T_R (T_\theta T_\theta^T) T_R \\ &= \frac{N}{2}\,\mathrm{diag}\left(2, 1, 1, \frac{1}{2^2}, \frac{1}{2^2}, \dots, \frac{1}{M^2}, \frac{1}{M^2}\right). \end{aligned}$$

Hence, we can see that $\|K_2\|_2 = \sqrt{N}$ and $\|K_2^{-1}\|_2 = \sqrt{2}M/\sqrt{N}$, which follows $\mathrm{cond}_2(K) = \sqrt{2}M$. □

We assume that the boundary is a circle. Then, in a manner similar to the decomposition of K, the matrix S can be decomposed as follows:

Proposition 5. *Let $\rho(\theta)$ be a constant ρ. Then, the matrix S can be decomposed into*

$$S = T_\theta^T S_{R_0},$$

where $S_{R_0} \in \boldsymbol{R}^{(2M+1)\times(2M+1)}$ is defined as

$$\begin{aligned} (S_{R_0})_{1,1} &= 1, \qquad (S_{R_0})_{k,j} = 0 \quad (k \neq j) \\ (S_{R_0})_{2k,2k} &= (S_{R_0})_{2k+1,2k+1} = \left(\frac{R_0}{\rho}\right)^k \quad (k = 1, 2, \dots, M). \end{aligned}$$

We obtain the following proposition and theorem by similar discussions to Propositions 3 and 4:

Proposition 6. *Let $N = 2M + 1$. Under the assumption in Proposition 5, the determinants of the matrices S_{R_0} and S can be given by*

$$\det(S_{R_0}) = \left(\frac{R_0}{\rho}\right)^{M(M+1)}, \qquad \det(S) = \frac{N^{M+1/2}}{2^M}\left(\frac{R_0}{\rho}\right)^{M(M+1)}.$$

Hence, S is not singular. Namely, the approximate solution by the MTM is uniquely determined.

Remark 5. We can solve (14) by Proposition 6. Using Propositions 2 and 5, $\boldsymbol{y} = S_{R_0}^{-1}(T_\theta^T)^{-1}\boldsymbol{f}$ can be written in the form:

$$\begin{aligned} a_0 &= \frac{1}{N}\sum_{j=1}^{N} g_j, \\ a_k &= \frac{2}{N}\left(\frac{\rho}{R_0}\right)^k \sum_{j=1}^{N} g_j \cos k\theta_j, \\ b_k &= \frac{2}{N}\left(\frac{\rho}{R_0}\right)^k \sum_{j=1}^{N} g_j \sin k\theta_j \quad (k = 1, 2, \dots, M), \end{aligned}$$

which correspond to the approximation to the coefficients of the Fourier series (11):

$$\begin{aligned} a_0 &= \frac{1}{2\pi}\int_0^{2\pi} f(\theta)\, d\theta, \\ a_k &= \frac{1}{\pi}\left(\frac{\rho}{R_0}\right)^k \int_0^{2\pi} f(\theta)\cos k\theta\, d\theta, \\ b_k &= \frac{1}{\pi}\left(\frac{\rho}{R_0}\right)^k \int_0^{2\pi} f(\theta)\sin k\theta\, d\theta, \quad (k = 1, 2, \dots, M). \end{aligned}$$

Theorem 1. *Under the assumption in Proposition 6, the condition number of S corresponding to the 2-norm is given as*

$$\mathrm{cond}_2(S) = \begin{cases} \sqrt{2}\left(\dfrac{\rho}{R_0}\right)^M & (R_0 < \rho) \\ \sqrt{2}\left(\dfrac{\rho}{R_0}\right) & (\rho \le R_0 < 2^{1/(2M)}\rho) \\ \left(\dfrac{R_0}{\rho}\right)^{M-1} & (2^{1/(2M)}\rho \le R_0 < \sqrt{2}\rho) \\ \dfrac{1}{\sqrt{2}}\left(\dfrac{R_0}{\rho}\right)^M & (R_0 \ge \sqrt{2}\rho) \end{cases}.$$

Proof. Since S_{R_0} and $T_\theta T_\theta^T$ are diagonal matrices, we can calculate

$$\begin{aligned} S^T S &= (T_\theta S_{R_0})^T (T_\theta S_{R_0}) = S_{R_0}(T_\theta T_\theta^T) S_{R_0} \\ &= \frac{N}{2} \operatorname{diag}\left(2, \left(\frac{R_0}{\rho}\right)^2, \left(\frac{R_0}{\rho}\right)^2, \ldots, \left(\frac{R_0}{\rho}\right)^{2M}, \left(\frac{R_0}{\rho}\right)^{2M}\right). \end{aligned}$$

Then, we know

$$\|S\|_2^2 = \frac{N}{2} \max\left\{2, \left(\frac{R_0}{\rho}\right)^2, \left(\frac{R_0}{\rho}\right)^{2M}\right\}$$

and

$$\|S^{-1}\|_2^2 = \left[\frac{N}{2} \min\left\{2, \left(\frac{R_0}{\rho}\right)^2, \left(\frac{R_0}{\rho}\right)^{2M}\right\}\right]^{-1}.$$

Hence, we derive

$$\|S\|_2 = \begin{cases} \sqrt{N} & (R_0 < 2^{1/(2M)}\rho) \\ \sqrt{\dfrac{N}{2}}\left(\dfrac{R_0}{\rho}\right)^M & (R_0 \geq 2^{1/(2M)}\rho) \end{cases}$$

and

$$\|S^{-1}\|_2 = \begin{cases} \sqrt{\dfrac{2}{N}}\left(\dfrac{\rho}{R_0}\right)^M & (R_0 < \rho) \\ \sqrt{\dfrac{2}{N}}\left(\dfrac{\rho}{R_0}\right) & (\rho \leq R_0 < \sqrt{2}\rho) \\ \dfrac{1}{\sqrt{N}} & (R_0 \geq \sqrt{2}\rho) \end{cases},$$

from which we obtain $\mathrm{cond}_2(S) = \|S\|_2 \|S^{-1}\|_2$. ☐

We denote the characteristic length R_0 that minimizes $\mathrm{cond}_2(S)$ by R_0^{opt}, which is called the optimal characteristic length. From Theorem 1, we obtain R_0^{opt} as follows:

Corollary 1. *Under the assumption in Theorem 1, the optimal characteristic length is given by*

$$R_0^{\mathrm{opt}} = 2^{1/(2M)}\rho.$$

Then, the minimal condition number of S is written as

$$\mathrm{cond}_2(S) = 2^{(M-1)/(2M)}. \tag{29}$$

We can see that (29) is a monotonically increasing function of M and is less than $\sqrt{2}$. Hence, the minimal condition number is less than $\mathrm{cond}_2(S) = \sqrt{2}$ for $R_0 = \rho$. On the other hand, if we consider the conventional Trefftz method ($R_0 = 1$) for the circular boundary whose radius is greater than 1 ($\rho > 1$), from Theorem 1 we have $\mathrm{cond}_2(S) = \sqrt{2}\rho^M$, which exponentially diverges for large M and ρ. Therefore, we know that the MTM is efficient.

From Propositions 1 and 5, we immediately obtain the following theorem:

Theorem 2. *Under the assumption in Theorem 1, the matrix SK corresponding to the MMFS can be decomposed into*

$$SK = T_\theta^T \Lambda T_\theta$$

with the diagonal matrix $\Lambda := S_{R_0} T_R \in \boldsymbol{R}^{(2M+1)\times(2M+1)}$ defined as

$$\Lambda_{1,1} = 1, \qquad \Lambda_{k,j} = 0 \quad (k \neq j)$$
$$\Lambda_{2k,2k} = \Lambda_{2k+1,2k+1} = -\frac{1}{k}\left(\frac{R}{\rho}\right)^k \quad (k = 1, 2, \ldots, M).$$

Therefore, the approximate solution by the MMFS is uniquely determined.

6. Numerical Experiments

6.1. Condition number corresponding to the MTM

We consider the following three domains (Figure 1):

$$\Omega_k = \{(r, \theta) : r = \rho^{(k)}(\theta),\ 0 \leq \theta < 2\pi\}, \qquad k = 1, 2, 3,$$

where $\rho^{(k)}(\theta)$ $(0 \leq \theta < 2\pi)$ are defined as

(a) circle: $\rho^{(1)}(\theta) = 1$; $(\rho_{\min}, \rho_{\max}) = (1, 1)$

(b) ellipse: $\rho^{(2)}(\theta) = ab/\sqrt{a^2 \sin^2\theta + b^2 \cos^2\theta}$ with $a = 10, b = 5$; $(\rho_{\min}, \rho_{\max}) = (5, 10)$

(c) epitrochoid: $\rho^{(3)}(\theta) = \sqrt{(a+b)^2 + 1 - 2(a+b)\cos(a\theta/b)}$ with $a = 3, b = 1$; $(\rho_{\min}, \rho_{\max}) = (3, 5)$

with $\rho_{\min} = \min\limits_{0\leq\theta<2\pi} \rho(\theta)$ and $\rho_{\max} = \max\limits_{0\leq\theta<2\pi} \rho(\theta)$.


(a) (b) (c)

Figure 1: Three domains

We can confirm that the numerical results for $k = 1$ which are shown below are proper by comparing them with the corresponding theoretical results obtained in the previous section.

Figure 2 shows the condition number $\mathrm{cond}_2(S)$ against $0 < R_0 \leq 15$ for each domain Ω_k $(k = 1, 2, 3)$ with $N = 21$ and $M = 10$.



Figure 2: Condition number of S against R_0 for each domain Ω_k $(N = 21, M = 10)$

From this result, we can observe that

$$\min_{0<R_0\leq 15} \mathrm{cond}_2(S) = \begin{cases} 1.366 & \text{at } R_0 = 1.035 \quad (k = 1) \\ 167.439 & \text{at } R_0 = 5.850 \quad (k = 2) \\ 39.481 & \text{at } R_0 = 3.636 \quad (k = 3) \end{cases}.$$

We can see that the minimal $\mathrm{cond}_2(S)$ and the corresponding R_0 for $k = 1$ coincide with the result of Corollary 1. When we use the conventional Trefftz method $(R_0 = 1)$, the condition number $\mathrm{cond}_2(S)$ for each domain Ω_k $(k = 1, 2, 3)$ with $N = 21$ and $M = 10$ can be obtain as follows:

$$\mathrm{cond}_2(S) = \begin{cases} 1.4142 & (k = 1) \\ 1.9430 \times 10^9 & (k = 2) \\ 3.6112 \times 10^6 & (k = 3) \end{cases}.$$

Hence, we can see that the choice of a suitable R_0 effects the drastic reduction of $\mathrm{cond}_2(S)$.



Figure 3: Optimal R_0 against N for each domain Ω_k

Figure 3 shows R_0^{opt} against N for each domain Ω_k. In this figure, R_0^{opt} seems to remain stable as N increases. We can observe that

$$R_0^{\mathrm{opt}} \geq \rho_{\min} = \min_{0 \leq \theta < 2\pi} \rho(\theta),$$

which is theoretically true when $k = 1$ since $R_0^{\mathrm{opt}} = 2^{1/(2M)}\rho = 2^{1/(N-1)}\rho$ is given by Corollary 1, and $R_0^{\mathrm{opt}} \approx \rho = 1$ for sufficiently large N. From this result, we can conclude that a suitable R_0 should be a little bit greater than $\rho_{\min}$.



Figure 4: $\mathrm{cond}_2(S)$ for R_0^{opt} against N for each domain Ω_k

Figure 4 shows $\mathrm{cond}_2(S)$ for R_0^{opt} against N for each domain Ω_k. Figure 5 shows $\mathrm{cond}_2(S)$ against N for each domain Ω_k when $R_0 = 1$. Comparing Figure 4 with Figure 5, we can confirm that the suitable characteristic length R_0 can drastically reduce the condition number.



Figure 5: $\mathrm{cond}_2(S)$ against N for each domain Ω_k ($R_0 = 1$)

6.2. Condition number of the transform matrix from the MMFS to the MTM



Figure 6: $\mathrm{cond}_2(K_1)$ v.s. $\mathrm{cond}_2(K_2)$ against R ($N = 21$)



Figure 7: $\mathrm{cond}_2(K_1)$ $(R = 0.5, 1.26)$ v.s. $\mathrm{cond}_2(K_2)$ against N

The matrix K depends only on (N, M, R, R_0). We notice that K is independent of Ω. Figure 6 shows both of $\mathrm{cond}_2(K_1)$ and $\mathrm{cond}_2(K_2)$ against R when $N = 21$. From this figure, we can observe that $\mathrm{cond}_2(K_1)$ has the minimal value 2.22 at $R = 1.26$, which is smaller than $\mathrm{cond}_2(K_2) = 14.1421$ at any R. But, we cannot always take R that minimizes $\mathrm{cond}_2(K_1)$ since the source radius R must be smaller than $\rho_{\min}$. Figure 7 shows both of $\mathrm{cond}_2(K_1)$ for $R = 0.5, 1.26$ and $\mathrm{cond}_2(K_2)$ against odd N. We see from Figures 6 and 7 that $\mathrm{cond}_2(K_2)$ is much smaller than $\mathrm{cond}_2(K_1)$ for most of R, from which we confirm the efficiency of K_2.

6.3. Comparison of the MTM, the MFS and the MMFS

We assume that the exact solution is given by

$$u(x,y) = \exp\left(\frac{x}{x^2+y^2}\right)\cos\left(\frac{y}{x^2+y^2}\right)$$

in the exterior domain $\Omega = \Omega_3$ outside the epitrochoid boundary defined in the beginning of the section. We confirm the asymptotic behavior of u at infinity:

$$\begin{aligned} u(x,y) &= \exp\left(\frac{x}{x^2+y^2}\right)\cos\left(\frac{y}{x^2+y^2}\right) \\ &= \exp\left(\frac{\cos\theta}{r}\right)\cos\left(\frac{\sin\theta}{r}\right) \\ &= \left[1 + \frac{\cos\theta}{r} + O\left(\frac{1}{r^2}\right)\right]\left[1 - \frac{1}{2}\left(\frac{\sin\theta}{r}\right)^2 + O\left(\frac{1}{r^4}\right)\right] \\ &= 1 + O(r^{-1}), \qquad r \to \infty, \end{aligned}$$

which does not satisfy the condition (3). Hence, we use the MFS to solve the exterior problem with respect to $\widetilde{u} := u - 1$, which satisfies (3). Then, we can obtain the approximate solution to $u = \widetilde{u} + 1$.

We apply the following five methods for solving the problem:

1. The MTM

   Solve $S\boldsymbol{y} = \boldsymbol{f}$ to substitute $\boldsymbol{y}$ into (11)

2. The conventional MFS with the conventional basis functions (CMFS-CBF)

   Solve $A\boldsymbol{w} = \boldsymbol{f}$ to substitute $\boldsymbol{w}$ into (5)

3. The conventional MFS with the modified basis functions (CMFS-MBF)

   Solve $\widehat{A}\boldsymbol{w} = \boldsymbol{f}$ to substitute $\boldsymbol{w}$ into (10)

4. The modified MFS with the conventional basis functions (MMFS-CBF)

   Solve $SK_2\boldsymbol{w} = \boldsymbol{f}$ to substitute $\boldsymbol{w}$ into (5)

5. The modified MFS with the modified basis functions (MMFS-MBF)

   Solve $SK_2\boldsymbol{w} = \boldsymbol{f}$ to substitute $\boldsymbol{w}$ into (10)

We take $(N, M) = (19, 9)$. First, we confirm the accuracy of the solution obtained by all the methods. The absolute error between the numerical and the exact solutions on the circle whose radius is r is defined as

$$e(r, \theta) = |\widetilde{u}(r\cos\theta, r\sin\theta) - u(r\cos\theta, r\sin\theta)|,$$

where $\widetilde{u}$ stands for the numerical solution by one of the five methods. Figure 8 shows the absolute errors $e(10, \theta)$ for $R = 0.5, 1$. We can see that the MMFS-MBF is the best accurate among all the methods.



Figure 8: Absolute error ($(R, N) = (1, 19)$, $r = 0.5$ (left), $r = 1$ (right))

Next, we confirm the accuracy of the solution obtained by all the methods in the whole exterior domain. We define the following maximum error:

$$e(r) := \max_{0 \le \theta < 2\pi} e(r, \theta).$$



(a) $(R,N) = (0.002,7)$ (b) $(R,N) = (0.2,11)$



(c) $(R,N) = (0.5,19)$ (d) $(R,N) = (1.2,19)$



(e) $(R,N) = (1.2,11)$ (f) $(R,N) = (1.0,19)$

Figure 9: Maximum errors $e(r)$ against the distance r from the origin

Figure 9 shows the errors $e(r)$ against $r \in [10, 10^{10}]$ with (a) $(R,N) = (0.002,7)$, (b) $(R,N) = (0.2,11)$, (c) $(R,N) = (0.5,19)$, (d) $(R,N) = (1.2,19)$, (e) $(R,N) = (1.2,11)$, (f) $(R,N) = (1.0,19)$. We can observe from the figure that the both of the errors for the CMFS-CBF and the MMFS-CBF increase as r increases, while the both of the errors for the CMFS-MBF and the MMFS-MBF decrease as r increases, Hence, we know that the modified basis functions are suitable for approximating the solution in the whole exterior domain.

Moreover, we can see from the same figure that in both of the cases where the conventional and the modified basis functions are used, the accuracy of the

MMFS is improved more than the accuracy of the conventional MFS.

For small r, the MMFS and the modified basis function do not always give better accuracy. But, they give much better accuracy by taking suitable parameters R and N. The accuracy of the MMFS-MBF is the best for the whole r in almost cases.

Therefore, we can conclude that the MMFS-MBF is the best method among the five methods if we need to obtain a highly accurate solution in the whole domain.

6.4. Condition numbers corresponding to the MFS and the MMFS



Figure 10: $\mathrm{cond}_2(A)$ v.s. $\mathrm{cond}_2(SK)$ against R ($N = 9$)



Figure 11: $\mathrm{cond}_2(A)$ v.s. $\mathrm{cond}_2(SK)$ against N $(R = 1.2)$

Figure 10 compares the condition numbers of A and SK corresponding to the CMFS and the MMFS, respectively, when $N = 9$. Figure 11 compares the condition numbers of A and SK for $R = 1.2$, from which we can observe $\mathrm{cond}_2(A) = 8.552 \times 2.752^N$ and $\mathrm{cond}_2(SK) = 1.248 \times 2.058^N$. Therefore, $\mathrm{cond}_2(SK)$ is smaller than $\mathrm{cond}_2(A)$. It is concluded that we can successfully reduce the condition number by using the MMFS.

7. Conclusions

We have proposed the MMFS with the modified basis functions for solving the exterior boundary value problem, based on the MTM. Under the assumption of the circular boundary, the condition number corresponding to the MTM is mathematically shown. Then, the optimal characteristic length R_0 that minimizes the condition number is given in the mathematical form. The uniqueness of the approximate solutions by the MTM and the MMFS is also proven.

The numerical experiments shows that the MMFS-MBF proposed in the paper is a more accurate method than the MTM, the CMFS-CBF and the CMFS-MBF. The condition number corresponding to the MMFS is smaller than the one corresponding to the CMFS. It is concluded that the MMFS-MBF is an efficient method.

As future works, we will give some mathematical expressions of condition numbers that are not given in this paper. More methodical approach than one in this paper will be appeared in another paper. It is important to prove the reason why the MMFS can improve the accuracy.

Acknowledgements

The authors gratefully acknowledge the financial support of the National Science Council of Taiwan through the grant No. NSC98–2811–E–002–092.

[1] Bogomolny A. Fundamental solutions method for elliptic boundary value problems. SIAM Journal on Numerical Analysis 1985; 22 (4): 644–669.

[2] Chen JT, Wu CS, Lee YT, Chen KH. On the equivalence of the Trefftz method and method of fundamental solutions for Laplace and biharmonic equations. Computers and Mathematics with Applications 2007; 53; 851–879.

[3] Chen JT, Lee YT, Yu SR, Shieh SC. Equivalence between the Trefftz method and the method of fundamental solution for the annular Green's function using the addition theorem and image concept. Engineering Analysis with Boundary Elements 2009; 33; 678–688.

[4] Katsurada M, Okamoto H. A mathematical study of the charge simulation method I. J. Fac. Sci. Univ. Tokyo, Sect. IA, Math. 1988; 35; 507–518.

[5] Katsurada M. A mathematical study of the charge simulation method II. J. Fac. Sci. Univ. Tokyo, Sect. IA, Math. 1989; 36; 135–162.

[6] Katsurada M, Okamoto U. The collocation points of the fundamental solution method for the potential problem. Computers & Mathematics With Applications 1996; 31 (1): 123–137.

[7] Liu CS. Improving the ill-conditioning of the method of fundamental solutions for 2D Laplace equation. CMES 2008; 28; 77–93.

[8] Mathon R, Johnston R L. The approximate solution of elliptic boundary-value problems by fundamental solutions. SIAM Journal on Numerical Analysis 1977; 14 (4): 638–650.

[9] Ramachandran PA. Method of fundamental solutions: singular value decomposition analysis. Communication in Numerical Methods in Engineering 2002; 18: 789–891.